

E-Card Instructions

1. Fold cardstock paper in half and create artwork on front.
2. Determine where light will go & gently poke a very small hole through the front of card.
3. Tape 2 pieces of conductive tape parallel on either side of the hole (inside card).
4. Label one piece of tape + (positive) and the other – (negative).
5. Push LED through hole. Tape shorter leg (-) to negative tape & longer leg (+) to positive tape. Make sure the end of leg is on tape.
6. Tape battery down (positive side down to positive tape). Use just a little tape, most of the battery needs to be uncovered.
7. Test light by laying final piece of conductive tape across battery & negative tape to complete the circuit.
8. Take backing off final piece of tape. Lay across battery & negative tape sticky side up. Close card, so it sticks to the opposite side.

